



## Specifications Osram SubstiTUBE LED T8 Advanced (EM Mains) Standard Output 7.3W 1100lm - 865 Daylight | 60cm - Replaces 18W

[View Product](#)

### General Information

|                             |                                     |
|-----------------------------|-------------------------------------|
| SKU                         | 238994                              |
| EAN                         | 4058075454767                       |
| Brand                       | Osram                               |
| Manufacturer Name           | ST8A-0.6M 7,3W/865 220-240V EM FLH1 |
| Full box quantity           | 10                                  |
| Any Lamp all-in warranty    | 5 Years                             |
| Energy efficiency class old | A++                                 |
| Average Lifetime (h)        | 50000                               |

### Technical Information

|                             |               |
|-----------------------------|---------------|
| Technology                  | LED           |
| Replaces (Watt)             | 18            |
| Wattage                     | 8             |
| Dimmable                    | Not Dimmable  |
| Cap / Base                  | G13           |
| Rotatable                   | No            |
| Colour Code                 | 865 Daylight  |
| Colour temperature (Kelvin) | 6500 Daylight |
| Colour Rendering (Ra)       | 80-89         |
| Colour of Light             | White         |

|                      |              |
|----------------------|--------------|
| Light colour options | Single Color |
|----------------------|--------------|

|                       |      |
|-----------------------|------|
| Luminous Flux (Lumen) | 1100 |
|-----------------------|------|

|                          |       |
|--------------------------|-------|
| Luminous Efficacy (lm/W) | 137.5 |
|--------------------------|-------|

|                       |             |
|-----------------------|-------------|
| Product Type Category | LED Tube T8 |
|-----------------------|-------------|

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Lamp Information

|                      |     |
|----------------------|-----|
| LED Starter included | Yes |
|----------------------|-----|

|                  |    |
|------------------|----|
| Requires Ballast | No |
|------------------|----|

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
|-----------------------|-----------------------------------------------------------------------|

|                 |                 |
|-----------------|-----------------|
| LED Tube Output | Standard Output |
|-----------------|-----------------|

|         |       |
|---------|-------|
| Housing | Glass |
|---------|-------|

|        |            |
|--------|------------|
| Series | Substitute |
|--------|------------|

## Dimensions

|        |      |
|--------|------|
| Length | 60cm |
|--------|------|

|             |     |
|-------------|-----|
| Length (mm) | 600 |
|-------------|-----|

|               |    |
|---------------|----|
| Diameter (mm) | 28 |
|---------------|----|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

