



## Specifications Osram SubstiTUBE LED T8 Advanced (EM Mains) Standard Output 14W 2100lm - 840 Cool White | 120cm - Replaces 36W

[View Product](#)

### General Information

|                             |                                    |
|-----------------------------|------------------------------------|
| SKU                         | 238995                             |
| EAN                         | 4058075454781                      |
| Brand                       | Osram                              |
| Manufacturer Name           | ST8A-1.2M 14W/840 220-240V EM FLH1 |
| Full box quantity           | 10                                 |
| Any Lamp all-in warranty    | 5 Years                            |
| Energy efficiency class old | A++                                |
| Average Lifetime (h)        | 30000                              |

### Technical Information

|                             |               |
|-----------------------------|---------------|
| Technology                  | LED           |
| Replaces (Watt)             | 36            |
| Wattage                     | 14            |
| Dimmable                    | Not Dimmable  |
| Cap / Base                  | G13           |
| Rotatable                   | No            |
| Colour Code                 | 865 Daylight  |
| Colour temperature (Kelvin) | 6500 Daylight |
| Colour Rendering (Ra)       | 80-89         |
| Colour of Light             | White         |

|                      |              |
|----------------------|--------------|
| Light colour options | Single Color |
|----------------------|--------------|

|                       |      |
|-----------------------|------|
| Luminous Flux (Lumen) | 2100 |
|-----------------------|------|

|                          |     |
|--------------------------|-----|
| Luminous Efficacy (lm/W) | 150 |
|--------------------------|-----|

|                       |             |
|-----------------------|-------------|
| Product Type Category | LED Tube T8 |
|-----------------------|-------------|

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Lamp Information

|                      |     |
|----------------------|-----|
| LED Starter included | Yes |
|----------------------|-----|

|                  |    |
|------------------|----|
| Requires Ballast | No |
|------------------|----|

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
|-----------------------|-----------------------------------------------------------------------|

|                 |                 |
|-----------------|-----------------|
| LED Tube Output | Standard Output |
|-----------------|-----------------|

|         |       |
|---------|-------|
| Housing | Glass |
|---------|-------|

|        |            |
|--------|------------|
| Series | Substitute |
|--------|------------|

## Dimensions

|        |       |
|--------|-------|
| Length | 120cm |
|--------|-------|

|             |      |
|-------------|------|
| Length (mm) | 1200 |
|-------------|------|

|               |    |
|---------------|----|
| Diameter (mm) | 28 |
|---------------|----|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

